

## IMAGE PICKUP APPARATUS

### BACKGROUND OF THE INVENTION

#### Field of the Invention

5           The present invention relates to an image pickup apparatus capable of picking up a dynamic image or a still image such as a video camera.

#### Related Background Art

10           In a digital color camera, in response to pressing down of a RELEASE button, an image in a field is exposed to a solid-state image pickup element such as a CCD or a CMOS sensor for a desired time period, an image signal thus obtained and representing a still image on a screen is converted into a digital signal  
15           and is subject to predetermined processing such as the YC processing, and an image signal of a predetermined format is obtained. Digital image signals representing the picked up images are recorded in a semiconductor memory on a picture basis. The recorded image signals  
20           are read according to the need to be reproduced as signals capable of being displayed or printed, and are outputted to a monitor or the like to be displayed.

          One example of a technology for thinning a digital color camera is disclosed in Japanese Patent  
25           Application Laid-Open No. 10-145802. In Japanese Patent Application Laid-Open No. 10-145802, an image pickup screen is divided into a plurality of regions,

008290" 4964-062800

and an imaging optical system is provided for each of the regions to form a partial image of an object.

Wherein one object image is formed with regard to one imaging optical system, and object images the number of which corresponds to the number of the divisions of the image pickup screen are projected onto a single image pickup element.

By arranging a plurality of small island-like image pickup regions and by providing each of them with a small-sized imaging system, a thinner image pickup apparatus can be materialized.

Generally, making larger the whole area of the image pickup element lowers the production yield, and, due to limitation on the cost, an upper limit is practically placed on the size of the image pickup element. When, as disclosed in the Japanese Patent Application Laid-Open No. 10-145802, small island-like image pickup regions are arranged for the purpose of thinning the image pickup apparatus and obtaining a high definition image, it is necessary to make small at least the pixel pitch of the image pickup element according to the sampling theory in order to make high the spatial frequency which can be represented by the photoelectric conversion output of the image pickup element.

In addition to this, an image pickup optical system for forming an object image on the image pickup

008290-49640960

element is required to have high contrast up to a higher frequency.

The imaging performance of an imaging system is represented by a response function referred to as OTF.

5 When the above characteristics are represented by the OTF characteristics, it is required that the response curve maintains high response from a low frequency to a high frequency and that once the response is lowered to zero, after that, the response does not have a value  
10 other than zero.

The phenomenon that the response becomes negative after it is once lowered to zero is referred to as spurious resolution which depends on the aberration characteristics of the image pickup optical system. At  
15 a spatial frequency where the response is negative, a portion which should be black becomes white while a portion which should be white becomes black, and thereby reversal of negative/positive occurs. An imaging system which causes spurious resolution has a  
20 strong tendency to have low response in a medium frequency range. Thus, the image as a whole does not have enough contrast and detailed portions are unnaturally represented. Then, such the imaging system is most inappropriate for recording a person or a  
25 scene.

There are two methods of improving the aberration characteristics of an image pickup optical system to

003290" 49640960

5

10

15

20

25

Therefore, conventionally, it is difficult to materialize a simply structured image pickup optical system which obtains a high definition image corresponding to a small pixel pitch.

5

#### SUMMARY OF THE INVENTION

According to one aspect of the present invention, there is provided an image pickup apparatus comprising a plurality of image pickup portions for receiving  
10 different wavelength components of object light, and a plurality of optical systems for guiding the object light to the plurality of image pickup portions, respectively, each of the plurality of optical systems having a filtering function whose transmission factor  
15 becomes smaller as the distance from an optical axis thereof becomes longer. The image pickup apparatus of the present invention is small-sized and has high image quality.

Other aspects of the present invention will become  
20 apparent from the following preferable specific embodiments.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a sectional view of an image pickup  
25 system of a digital color camera according to an embodiment of the present invention;

Fig. 2 is a front view of a solid-state image

003290" 49640950

Fig. 3 is a front view of a diaphragm of the image pickup system shown in Fig. 1;

Fig. 5 illustrates an objective lens of the image pickup system shown in Fig. 1 which is viewed from the side where light is projected;

Fig. 7 is a graph showing the spectral transmission factor characteristics of a color purity correction filter of the image pickup system shown in Fig. 1;

Fig. 9 is a graph showing the transmission factor distribution of a transmission factor distribution type filter of the image pickup system shown in Fig. 1;

Fig. 11 is a graph showing the intensity

distribution in an image by the image pickup system shown in Fig. 1;

Fig. 12 is an explanatory view for explaining the setting of the intervals between lens portions of the image pickup system shown in Fig. 1;

Fig. 13 is an explanatory view for explaining the positions of images of an object at infinity of the image pickup system shown in Fig. 1;

Fig. 14 is a block diagram of a signal processing system of the digital color camera shown in Fig. 1;

Fig. 15 illustrates the positional relationship of the image pickup region for R and B pixels with respect to the image pickup region for a G pixel of the image pickup system shown in Fig. 1;

Fig. 16 is an explanatory view of interpolation processing of the digital color camera shown in Fig. 1;

Figs. 17A, 17B, and 17C illustrate the overall structure of the digital color camera shown in Fig. 1;

Fig. 18 is a graph showing a transmission factor distribution of a transmission factor distribution type filter according to a second embodiment of the present invention;

Fig. 19 is a front view of the transmission factor distribution type filter shown in Fig. 18;

Fig. 20 is a graph showing a transmission factor distribution of another transmission factor distribution type filter according to the second

003290-49540960

embodiment of the present invention;

Fig. 21 is a sectional view of an image pickup system according to a third embodiment of the present invention; and

5 Fig. 22 is a sectional view of another image pickup system according to the third embodiment of the present invention.

#### DESCRIPTION OF THE PREFERRED EMBODIMENTS

10 Preferred embodiments of the present invention are now described in detail with reference to the drawings.

First of all, the structure as a whole of a digital color camera using the present invention and its signal processing system are described.

15 Figs. 17A, 17B, and 17C illustrate the overall structure of a digital color camera according to a first embodiment of the present invention. Figs. 17A, 17C, and 17B are a front view, a rear view, and a sectional view taken along the line 17B-17B in the rear  
20 view of Fig. 17C, respectively.

In Figs. 17A, 17B, and 17C, reference numeral 1 denotes a camera body. An illuminating light intake window 2 formed of a white diffusing plate is positioned at the back of a color liquid crystal  
25 monitor 4. Reference numerals 5 and 6 denote a main switch and a RELEASE button, respectively. Reference numerals 7, 8, and 9 are switches for a user to set the

008290-49640960



state of the camera. In particular, the reference numeral 9 denotes a PLAY button. A reference numeral 13 denotes a display of the remaining number of recordable pictures. Object light which is incident into a prism 12 from a viewfinder front frame 3 is projected from a viewfinder eyepiece window 11. Reference numerals 10 and 14 denote an image pickup system and a connection terminal for connecting to an external computer or the like to transmit and receive data, respectively.

The schematic structure of a signal processing system is now described. Fig. 14 is a block diagram of the signal processing system. This camera is a single plate type digital color camera using a solid-state image pickup element 120 such as a CCD or a CMOS sensor. Image signals representing a dynamic image or a still image are obtained by driving the solid-state image pickup element 120 continuously or only once. Here, the solid-state image pickup element 120 is an image pickup device of the type which converts exposed light into electric signals with regard to the respective pixels, stores respective charges according to the light amount, and reads the respective charges.

It is to be noted that Fig. 14 only shows portions which are directly relevant to the present invention, and illustration and description of portions which are not directly relevant to the present invention are

omitted.

As shown in Fig. 14, the image pickup apparatus has the image pickup system 10, an image processing system 20 as an image processing means, a recording and reproduction system 30, and a control system 40.

Further, the image pickup system 10 includes therein an objective lens 100, a diaphragm 110, and the solid-state image pickup element 120, the image processing system 20 includes therein an A/D converter 500, an RGB image processing circuit 210, and a YC processing circuit 230, the recording and reproduction system 30 includes therein a recording processing circuit 300 and a reproduction processing circuit 310, and the control system 40 includes therein a system control unit 400, an operation detection circuit 410, and a drive circuit 420 of the solid-state image pickup element.

The image pickup system 10 is an optical processing system for imaging light incident from an object through the diaphragm 110 and the objective lens 100, on an image pickup plane of the solid-state image pickup element. The light transmission factor of the objective lens 100 is adjusted to expose a subject image of an appropriate light amount to the solid-state image pickup element 120. As described in the above, as the solid-state image pickup element 120, an image pickup device such as a CCD and a CMOS sensor is applied. By controlling the exposure time and the

exposure intervals of the solid-state image pickup element 120, image signals representing continuous dynamic images or image signals representing a still image by one exposure can be obtained.

5           Next, the image pickup system 10 is described. In the present embodiment, the objective lens 100 which is an image pickup optical system of the image pickup system 10 is provided with transmission factor distribution type filters 54a, 54b, and 54c which are  
10           optical filtering means according to the present invention.

          Fig. 1 is a detailed view of the image pickup system 10. First, the diaphragm 110 has three circular openings 110a, 110b, and 110c as shown in Fig. 3.  
15           Object light which enters a light incidence plane 100e of the objective lens 100 from the openings are projected from three lens portions 100a, 100b, and 100c of the objective lens 100 to form three object images on the image pickup plane of the solid-state image  
20           pickup element 120. The diaphragm 110, the light incidence plane 100e, and the image pickup plane of the solid-state image pickup element 120 are in parallel with one another. In this way, by making weak the  
25           power on the incidence side, making strong the power on the projection side, and providing a diaphragm on the incidence side, the curvature of the image plane can be made less. It is to be noted that, though the light

00604964.062800  
008290" 49640960

incidence plane 100e of the objective lens 100 is a plane here, the light incidence plane 100e may be formed of three spherical surfaces or three rotation-symmetry nonspherical surfaces.

5           The three lens portions 100a, 100b, and 100c have circular spherical surface portions as shown in Fig. 5 showing the objective lens 100 viewed from the side where light is projected. An infrared radiation cutting filter having a low transmission factor with regard to the wavelength range of 670 nm and more is formed on the spherical surface portions while a light-shielding film is formed on a plane portion 100d shown with hatching. More specifically, the objective optical system is formed with the objective lens 100 and the diaphragm 110, while the three lens portions 100a, 100b, and 100c are the imaging system.

20           The manufacturing is easy with using glass molding in case the objective lens 100 is made of glass and with using injection molding in case the objective lens 100 is made of resin.

25           Fig. 2 is a front view of the solid-state image pickup element 120. The solid-state image pickup element 120 is provided with three image pickup regions 120a, 120b, and 120c corresponding to the formed three object images. Each of the image pickup regions 120a, 120b, and 120c are sized to be 2.24 mm × 1.68 mm with the arrangement of 800 × 600 pixels having the vertical

008290" 49640960

and horizontal pitch of 2.8  $\mu\text{m}$ . The size of the whole image pickup regions is 2.24 mm  $\times$  5.04 mm. The diagonal size of each of the image pickup regions is 2.80 mm. In the figure, image circles 51a, 51b, and 51c within which an object image is formed are circular, the sizes of which circles are determined by the size of the openings of the diaphragm and the spherical surface portions on the projection side of the objective lens 100. The image circles 51a and 51b overlap each other and the image circles 51b and 51c overlap each other.

In Fig. 1, hatched portions 52a, 52b, and 52c sandwiched between the diaphragm 110 and the objective lens 100 are optical filters formed on the light incidence plane 100e of the objective lens 100. As shown in Fig. 4 showing the objective lens 100 viewed from the light incidence side, the optical filters 52a, 52b, and 52c are formed in regions which completely include the diaphragm openings 110a, 110b, and 110c, respectively.

The optical filter 52a has spectral transmission factor characteristics shown as G in Fig. 6 which mainly transmit green, the optical filter 52b has spectral transmission factor characteristics shown as R which mainly transmit red, and the optical filter 52c has spectral transmission factor characteristics shown as B which mainly transmit blue, and thus, these are

primary color filters. As the product with the characteristics of the infrared radiation cutting filter formed on the lens portions 100a, 100b, and 100c, the object images formed in the image circles 51a, 51b, and 51c are of green light component, red light component, and blue light component, respectively.

On the other hand, optical filters 53a, 53b, and 53c are formed on the three image pickup regions 120a, 120b, and 120c, respectively, of the solid-state image pickup element 120. Their spectral transmission factor characteristics are equivalent to the ones shown in Fig. 6. More specifically, the image pickup regions 120a, 120b, and 120c are sensitive to green light (G), red light (R), and blue light (B), respectively.

Since the spectral distributions of the received light of the respective image pickup regions are given as the product of the spectral transmission factors of the pupils and the spectral transmission factors of the image pickup regions, respectively, the combination of the pupil and the image pickup region is selected according to the wavelength range. More specifically, object light which goes through the diaphragm opening 110a is mainly photoelectrically converted in the image pickup region 120a, object light which goes through the diaphragm opening 110b is mainly photoelectrically converted in the image pickup region 120b, and object

000290"49640960

light which goes through the diaphragm opening 110c is mainly photoelectrically converted in the image pickup region 120c. In other words, the image pickup regions 120a, 120b, and 120c output a G image, an R image, and a B image, respectively. In this way, by using multiple optical filters for the purpose of color separation on the pupils of the image pickup optical system and on the image pickup element, the color purity can be enhanced. This is because, by using the same kind of optical filters twice, the buildup of the transmission factor characteristics becomes steeper and the red color (R) and the blue color (B) do not overlap each other. It is to be noted that the transmission factors of the optical filters 52a, 52b, and 52c or of the optical filters 53a, 53b, and 53c are preferably set so as to provide appropriate signal levels in the respective image pickup regions in the same accumulation time.

In the image processing system 20, a color image is formed based on the selective photoelectric conversion output obtained from the plurality of images by the plurality of image pickup regions of the solid-state image pickup element 120, respectively. Here, since the peak wavelength of the spectral luminous efficiency is 555 nm, the signal processing is carried out using a G image signal including this wavelength, as the reference image signal.

When the pixel pitch of the solid-state image pickup element is fixed, compared with a system adopted generally by a digital color camera in which an RGB color filter is formed on the solid-state image pickup element with, for example,  $2 \times 2$  pixel block basis to provide wavelength selectability to each pixel, and thus, an object image is separated into RGB images, the size of the object image is  $1/\sqrt{3}$  times, and thus, the focal length of the objective lens is about  $1/\sqrt{3}$  times, which is quite advantageous in thinning the camera.

It is to be noted that, with regard to the spectral transmission factor characteristics of the optical filters 52a, 52b, and 52c and of the optical filters 53a, 53b, and 53c, as shown in Fig. 6, R and G overlap each other and G and B overlap each other, though R and B are almost separated from each other.

Therefore, even when the image circle 51b of the red light overlaps the image pickup region 120c for photoelectrically converting the blue light, and conversely, even when the image circle 51c of the blue light overlaps the image pickup region 120b for photoelectrically converting the red light, these images do not become the output of the image pickup regions. However, at the portion where the image circle 51b of the red light overlaps the image pickup region 120a for photoelectrically converting the green light and at the portion where the image circle 51a of



the green light overlaps the image pickup region 120b for photoelectrically converting the red light, a small amount of an image of a different wavelength which should be blocked is superimposed. More specifically, since the selectivity of the object image is given by the product of the spectral transmission factor characteristics of the optical filter 52a and the spectral transmission factor characteristics of the optical filter 53b, and by the product of the spectral transmission factor characteristics of the optical filter 52b and the spectral transmission factor characteristics of the optical filter 53a, the cross talk of the R image signal and the G image signal does not become zero although it is small.

Therefore, the objective lens 100 is further provided with characteristics to lower the transmission factor of the wavelength range of the portion where R and G overlap each other. This can be carried out by using optical filtering technology implemented by a color purity correction filter.

The color purity correction filter is an optical filter formed of a base material made of a transparent synthetic resin or glass having a predetermined amount of rare-earth metal ions contained therein.

As the rare-earth metal ions, one or more selected among neodymium ions, praseodymium ions, erbium ions, holmium ions are used. However, it is preferable that

008290-49540960

at least neodymium ions are used as indispensable ions. It is to be noted that trivalence ions are generally used as these ions. The content of the metal ions is selected in a range of normally 0.01 to 40 mass parts, preferably 0.04 to 30 mass parts relative to 100 mass parts of the base material of the objective lens 100.

As shown in Fig. 7, the color purity correction filter has characteristics to selectively absorb light in a predetermined wavelength range between the peak wavelengths of the color components of R, G, and B to decrease the amount of transmission thereof. This action almost eliminates cross talk due to the overlap of the image circle 51b of the red light and the image pickup region 120a for photoelectrically converting the green light and the overlap of the image circle 51a of the green light and the image pickup region 120b for photoelectrically converting the red light.

Further, the objective lens 100 is also provided with photochromic characteristics which is a phenomenon to be darkened by light and to be reversibly achromatized when the irradiation of light is stopped. This is for, since the accumulation time control range of the solid-state image pickup element 120 is limited, suppressing the amount of light reaching the solid-state image pickup element when the field is extremely bright, thereby enlarging the recordable intensity range.

008290"49640960

As the photochromic glass, for example,  
photochromic glass of phosphate glass made by Chance-  
Pilkington which has been put to practical use for  
spectacles (Product name: Reactolite Rapide) may be  
5 used.

Fig. 8 is a graph showing the spectral  
transmission factor characteristics of a photochromic  
glass used as the objective lens 100. In Fig. 8, a  
solid line shows the characteristics after exposure to  
10 sunlight for 20 minutes while a broken line shows the  
characteristics with no exposure to sunlight. When the  
camera is carried about with the user outdoors under a  
blue sky or the like, light beams which enter the  
objective lens 100 from the diaphragm 110 makes the  
15 objective lens 100 itself darkened to suppress the  
amount of light entering the solid-state image pickup  
element 120 to be about 1/2. As a result, the  
accumulation time can be made twice as long, which  
raises the control limitation on the high intensity  
20 side.

The screen size of each of the image pickup  
regions 120a, 120b, and 120c is 2.24 mm × 1.68 mm as  
described in the above, since the pixel pitch is 2.8 μm  
and the number of the pixels are 800 × 600. The  
25 diagonal screen size of each of the image pickup  
regions is 2.80 mm. Generally, when the image pickup  
angle θ of a small-sized camera is about 70° in the

008290-49640960

diagonal direction, the camera is most convenient.

When the image pickup angle is  $70^\circ$ , the focal length is 2.0 mm in this case, since it is determined by the diagonal size of the screen.

5           When a person or the like is the subject of recording, considering that a person is about 170 cm tall and one person to three people are often recorded at a time, a virtual distance  $D$  to the subject [m] can be defined as in the following equation (1) as a  
10           function of the image pickup angle  $\theta[^\circ]$ :

$$D = 1.4 / \tan (\theta/2) \quad \dots (1)$$

          Substituting  $70^\circ$  for  $\theta$  of equation (1),  $D = 2.0$  m is obtained. Here, if the image pickup system 10 is formed so as to focus on the subject best when the  
15           distance to the subject is 2 m, the letting out of the lens from the point at infinity is 0.002 mm. Taking into consideration the allowable circle of confusion to be described later, there causes practically no problem even if the image pickup system is a fixed focus image  
20           pickup optical system without a mechanism for letting the lens out.

          A focal length  $f$  of a planoconvex lens put in the air can be represented as follows:

$$f = \{1 / (1-n)\} r \quad \dots (2)$$

25           wherein  $n$  is the index of refraction and  $r$  is the radius of the spherical surface. Therefore, if the index of refraction  $n$  of the objective lens 100 is 1.5,

009290" 49640950

for example,  $r$  for obtaining the focal length of 2.0 mm is 1.0 mm.

It is convenient to make equal the sizes of the red, green, and blue object images, since there is no need to make correction of the image magnification, and thus, the processing time is not elongated. Therefore, the lens portions 100a, 100b, and 100c are optimized for the peak wavelengths of 530 nm, 620 nm, and 450 nm of the lights which go through the RGB optical filters, respectively to make equal the magnifications of the respective images. This can be paraxially materialized by making equal the distance from the positions of the principal points of the respective lens portions to the solid-state image pickup element.

In case of glass with the index of refraction of the d line (587.6 nm)  $n_d = 1.5$  and the Abbe number  $v_d = 60$ , the indexes of refraction at the wavelengths of 530 nm, 620 nm, and 450 nm are about 1.503, 1.499, and 1.509, respectively. If all the radii  $r$  of the spherical surfaces of the lens portions 100a, 100b, and 100c equal -1.0 mm, the focal lengths at the respective wavelengths are, by the equation (2), as follows:

the lens portion 100a having the representative wavelength of 530 nm : 1.988 mm,

the lens portion 100b having the representative wavelength of 620 nm : 2.004 mm, and

the lens portion 100c having the representative

wavelength of 450 nm : 1.965 mm.

Suppose from the pixel pitch that the allowable circle of confusion is 3.0  $\mu\text{m}$  and further suppose that the f-number of the objective lens is F5.6, the depth of focus represented as the product of the two is 16.8  $\mu\text{m}$ . It can be seen that the difference 0.039 mm between the focal length in case of 620 nm and the focal length in case of 450 nm already exceeds this.

More specifically, though the paraxial image magnifications are the same, depending on the color of the subject, the subject may be out of focus. Since the spectral transmission factor of an object normally ranges over a wide wavelength range, it is quite rare that a sharp image in focus can be obtained.

Accordingly, the radii  $r$  of the spherical surfaces of the lens portions 100a, 100b, and 100c are optimized with regard to the respective representative wavelengths. More specifically, here, no achromatism for removing the chromatic aberration over the whole visible region is not carried out and designs for the wavelengths are applied to the respective lenses. First, the equation (2) is transformed to obtain the following equation (3):

$$r = (1-n) f \quad \dots (3)$$

Inserting  $f = 2.0$  and inserting in sequence  $n = 1.503$ ,  $n = 1.499$ , and  $n = 1.509$  in the equation (3), the following respective radii are calculated:

008290"49540960

the lens portion 100a having the representative wavelength of 530 nm :  $r = -1.006$  mm,

the lens portion 100b having the representative wavelength of 620 nm :  $r = -0.998$  mm, and

5 the lens portion 100c having the representative wavelength of 450 nm :  $r = -1.018$  mm.

In order to make well-balanced the difference in the image magnifications at a high position of an image, the heights of the vertices of the lens portions 100a, 100b, and 100c are slightly adjusted, and then, both the sharpness and the image magnification are ideal. Further, non-spherical surfaces are used for the respective lens portions to satisfactorily correct the curvature of the image plane. With regard to the distortion of the image, it can be corrected in the signal processing to be carried out later.

In this way, when reference G image signals by the green object light including the wavelength of 555 nm which has the highest luminosity factor and image signals by the red and blue object lights, respectively, are obtained, and different focal lengths are set (the lens portions 100a to 100c are set at different focal length with regard to light other than the spectral distributions having the above representative wavelengths) with regard to one wavelength (for example, green of the wavelength of 555 nm having the highest luminosity factor) and a

008290"49640960

15 *Invst* The objective lens 100 is required to have high contrast image dissection up to the spatial frequency range as high as the pixel pitch. The image pickup system 10 takes in three object images with regard to the three wavelength ranges, and thus, compared with an image pickup system provided with a mosaic optical filter such as of the Baiyer arrangement having the same number of pixels, as described in the above, the focal length is about  $1/\sqrt{3}$  times to attain the same image pickup angle. Therefore, it is necessary to materialize high contrast image dissection of higher spatial frequency component. The optimization with regard to the respective wavelengths of the lens portions described in the above is a technology for



a'  
com

suppressing the chromatic aberration for the purpose of materializing this.

Generally, there are two methods of improving the aberration characteristics of an image pickup optical system to make spurious resolution less liable to occur, thereby alleviating problems: one is to increase the degree of freedom in designing by, for example, increasing the number of lenses forming the system, by making the lenses nonspherical, using anomalous dispersion glass, or by complexly using diffraction optical elements; and the other is to make narrower the imaging light beam.

The former method, that is, increase of the degree of freedom in designing is, though the focal length is  $1/\sqrt{3}$  times, toward complexity of the structure of the objective optical system, which goes against thinning of the image pickup apparatus, and thus, is inappropriate. On the other hand, the latter method, that is, use of a narrower light beam conforms to a thin image pickup apparatus.

When an imaging light beam is made narrower, as shown by a solid line b in Fig. 10, the response function referred to as OTF presents gradual monotone decrease in the low frequency component, and after that, becomes slightly negative, and then, becomes slightly positive. On the other hand, in case a broad light beam without narrowing is used, as shown by a

008290" 49640960

5           The state where the OTF is negative indicates  
occurrence of spurious resolution. This corresponds to  
an actual state where reversal of negative/positive  
occurs, that is, a portion which should be white is  
black while a portion which should be black is white.  
0   It makes it clear that a natural image can be obtained  
by making narrower the imaging light beam.

However, when the imaging light beam is extremely narrowed, the contrast in a high frequency range is decreased due to diffraction of light. In this state, an image is formed of a bright spot at the center and diffraction stripes surrounding the bright spot. These are caused by, as known well, relative increase in the intensity of the diffraction stripes due to peripheral waves generated on the periphery of the opening of the diaphragm.

The diffraction stripes can be decreased by adding to the objective lens a filter which is transparent at the center and becomes darker toward the periphery. This method is referred to as apodization, which is described in detail on pages 172 to 174 of "Kogaku Gijutsu Handbook Zohoban (Handbook of Optical Technology, Enlarged Edition)" (1975, Asakura Shoten).

Fig. 9 is a graph showing the transmission factor distribution of transmission factor distribution type filters provided on the light incidence plane 100e of the objective lens 100 so as to face the diaphragm openings 110a, 110b, and 110c. The transmission factor distribution type filters are denoted as 54a, 54b, and 54c in Fig. 1. The positions where the transmission factor is the highest correspond to the centers of the diaphragm openings 110a, 110b, and 110c while the positions where the transmission factor is zero correspond to the periphery of the openings 110a, 110b, and 110c, respectively, of the diaphragm. In other words, the transmission factor is distributed so as to be the highest at the centers of the diaphragm openings and so as to monotonically decrease toward the periphery.

Such a transmission factor distribution type filter is formed by forming a thin film of Inconel, Chromel, chromium or the like by vapor deposition or sputtering on the light incidence side of the objective lens 100. The characteristics shown in Fig. 9 can be obtained by making the thin film the thinnest at the center and the thickest on the periphery. It is to be noted that, in forming such a thin film, the position of a mask used in the vapor deposition or sputtering is continuously controlled.

Though the transmission factor distribution type

008290"49640950

filters 54a, 54b, and 54c are formed on the objective lens here, the structure may be that they are formed on a glass plate and are arranged on the light incidence side or the light projection side of the objective lens 100.

Fig. 11 is a graph showing the intensity distribution in an image. In the figure, a broken line a shows a case where the transmission factor is constant over the whole diaphragm opening, while a solid line b shows a case where the transmission factor is decreased from the center of the diaphragm opening toward the periphery. Compared with the case of the characteristics shown by a, there is no bound on the periphery of the image in the characteristics shown by b, which clearly shows that the image formed is satisfactory. Here, This reflects technological advantage of decreasing the diffraction stripes by decreasing peripheral light beams by means of apodization.

Next, the relationship between the objective lens and the image pickup regions is described. Since the image pickup system has three lens portions, the positions of the three object images relatively change according to the distance to the subject. As described in the above, each of the image pickup regions is sized to be 2.24 mm × 1.68 mm, and the image pickup regions are arranged adjacent to each other with their long

sides being in contact with each other. Therefore, the center to center distance of adjoining image pickup regions is 1.68 mm. In the YC processing circuit 230 to be described later, signal processing is carried out on the assumption that the center of an object image is the center of the image pickup region. When an object image with the virtual object distance of 2 m is to be formed on the image pickup portion at the same intervals as that distance, as shown in Fig. 12, the interval between the lens portions 100a and 100b and between the lens portions 100b and 100c is set to be 1.6783 mm. In the figure, arrows 55a, 55b, and 55c denote imaging systems having positive power by the three lens portions 100a, 100b, and 100c of the objective lens 100, respectively, rectangles 56a, 56b, and 56c denote the ranges of the image pickup regions 120a, 120b, and 120c, respectively, and L1, L2, and L3 are optical axes of the imaging systems 55a, 55b, and 55c, respectively. Since the light incidence surface of the objective lens 100 is a plane and the lens portions 100a, 100b, and 100c to be the light projection surface are spherical surfaces, perpendiculars from the respective centers of the spheres to the light incidence plane 100e are the optical axes.

Here, as shown in Fig. 13, images of an object at infinity are formed at the same intervals as that of

008250"4964.062800

the lens portions 100a, 100b, and 100c, and thus, the interval between the G object image and the R object image and the interval between the R object image and the B object image are 1.6783 mm, which is a little smaller than the center-to-center distance of the image pickup regions of 1.68 mm. The difference  $\Delta Y$  is 0.0017 mm, i.e., 1.7  $\mu\text{m}$ . With the G object image which has the highest luminosity factor being as the reference object image, when the B object image moves, the difference  $\Delta Y$  is doubled and is 3.4  $\mu\text{m}$ . Since it is often the case that a short-range object such as a person is positioned in the middle of a picture to be picked up and that a long-range object is positioned on the periphery of the picture, and, since the aberration of the objective lens increases on the periphery of the picture to lower the quality of an image, it can be understood that there is practically no problem if the maximum image interval change is smaller than the pixel pitch multiplied by two. As described in the above, since the pixel pitch P of the solid-state image pickup element 120 is 2.8  $\mu\text{m}$ , it follows that  $\Delta Y < 2 \times P$ , and thus, the color misalignment in an image at infinity to this extent is allowable.

Further, the interval between the images varies also according to temperature change of the image pickup system 10. Since the imaging magnification of the image pickup system 10 is extremely small, the

008290-19640960

$$Z = 1.68 \times (\alpha_L - \alpha_S) \times \Delta T \quad \dots (4)$$

10            Here, when  $\alpha S = 0.26 \times 10^{-5}$ ,  $\Delta T = 20[^\circ\text{C}]$ , and the  
objective lens 100 is formed of low-melting glass and  
 $\alpha L = 1.2 \times 10^{-5}$ ,  $\Delta Z$  is calculated at 0.00032 [mm]. This  
is the variation in the interval between the G object  
image and the R object image and the variation in the  
15 interval between the R object image and the B object  
image.

When the B object image is regarded as a variation with respect to the G object image which is the reference image signals, since the interval between the images is  $1.68 \times 2$ , the image interval variation is  $\Delta Z \times 2 = 0.00063$  [mm]. When the temperature range where the camera is used is 0 to 40°C, the deviation  $\Delta T$  from the reference temperature of 20°C is 20°C. Here, if  $\Delta Z \times 2$  is smaller than 1/2 of the pixel pitch, there is practically no problem. Generally, the coefficient of linear expansion  $\alpha_S$  of the solid-state image pickup element 120 is as small as about  $0.26 \times 10^{-5}$ , it is

necessary to select the coefficient of linear expansion  $\alpha_L$  of the objective lens 100 so as to satisfy the following expression (5):

$$2 \times A \times (\alpha_L - 0.26 \times 10^{-5}) \times 20 < 1/2 P \quad \dots (5)$$

5 wherein A is either the interval between the G image and the R image or the interval between the R image and the B image and P is the pixel pitch.

10 Since the coefficient  $\alpha_L (= 1.2 \times 10^{-5})$  of linear expansion of the objective lens 100 used in the above satisfies the relationship expressed by the expression (5), it can be understood that the material of the lens 100 is suitable for the camera.

15 Further, apart from the fluctuation of the image interval due to the distance to the object and due to temperature change, a method referred to as pixel shift is used where, by shifting relatively the image pickup regions 120a, 120b, and 120c of the solid-state image pickup element by 1/2 pixel, the resolution is made higher with a small number of pixels. The amount of  
20 the shift of 1/2 pixel is set with regard to the virtual object distance of 2 m.

As shown in Fig. 15, the image pickup region 120b for outputting the R image signals and the image pickup region 120c for outputting the B image signals are  
25 arranged so as to be shifted by 1/2 pixel both in the horizontal direction and in the vertical direction with respect to the image pickup region 120a for outputting

003250-49640560



5

10

15

20

25

As described in the above, an image pickup device having 1,800 pixels in its lengthwise direction and 800

5

10

20

25

resolution higher by interpolation.

The YC processing circuit 230 is a signal processing circuit for generating a luminance signal Y and chrominance signals R-Y and B-Y. The YC processing circuit 230 is formed of a high luminance signal generating circuit for generating high luminance signal YH, a low luminance signal generating circuit for generating a low luminance signal YL, and a chrominance signal generating circuit for generating chrominance signals R-Y and B-Y. A luminance signal Y is formed by compositing a high luminance signal YH and a low luminance signal YL.

The RGB image processing circuit 210 is now described in detail.

RGB signals outputted through the A/D converter 500 with regard to the R, G, and B regions, respectively, are first subject to predetermined white balance adjustment in the white balance circuit in the RGB image processing circuit 210, and then are subject to predetermined gamma control in the gamma control circuit.

The interpolation circuit in the RGB image processing circuit 210 generates by interpolation, image signals having the resolution which is four times as much as that of the 600 × 800 pixels, converts the image signals from the solid-state image pickup element 120 into signals having high definition image quality,

008290 49640960

and supplies them to the high luminance signal generating circuit, the low luminance signal generating circuit, and the chrominance signal generating circuit at the subsequent stage.

5           Since the sizes of the R, G, and B object images are already the same based on the setting of the objective lens 100, first, by a publicly known method, arithmetic processing for correcting optical aberration of the objective optical system is carried out with  
10       regard to the respective image signals. After that, the interpolation processing, the luminance signal processing, and the chrominance signal processing which are the same as those of an ordinary digital color camera are performed. The interpolation processing is  
15       as follows.

          First, a G image signal which is a reference image signal from the image pickup region 120a is subject to interpolation according to the following equations (6) to (9):

20            $G_{2i2j} = G_{ij} \quad \dots (6)$

$G_{2i(2j+1)} = G_{ij} \cdot 1/2 + G_{i(j+1)} \cdot 1/2 \quad \dots (7)$

$G_{(2i+1)2j} = G_{ij} \cdot 1/2 + G_{(i+1)j} \cdot 1/2 \quad \dots (8)$

$G_{(2i+1)(2j+1)} = G_{ij} \cdot 1/4 + G_{i(j+1)} \cdot 1/4 +$   
 $G_{(i+1)j} \cdot 1/4 + G_{(i+1)(j+1)} \cdot 1/4 \quad \dots (9)$

25       This is, 16G elements are generated from each four G pixels, and thus the G image signals of 600 x 800 pixels from the image pickup region 120a are converted

008290"49640960

into 1200 x 1600 pixels.

Then, R image signals from the image pickup region 120b corresponding to the respective positions of the G image signals calculated using the above equations (6)

5 to (9) are subject to interpolation according to the following equations (10) to (13):

$$\begin{aligned} R_{2i2j} = & R(i-1)(j-1) \cdot 1/4 + R(i-1)j \cdot 1/4 + \\ & R i(j-1) \cdot 1/4 + R_{ij} \cdot 1/4 \quad \dots (10) \end{aligned}$$

$$R_{2i(2j+1)} = R(i-1)j \cdot 1/2 + R_{ij} \cdot 1/2 \quad \dots (11)$$

10  $R(2i+1)2j = R i(j-1) \cdot 1/2 + R_{ij} \cdot 1/2 \quad \dots (12)$

$$R(2i+1)(2j+1) = R_{ij} \quad \dots (13)$$

Since, as described in the above, the image pickup region of the R object image and the image pickup region of the B object image are arranged so as to be  
15 shifted by 1/2 pixel from the image pickup region of the G object image, the original output of the ij address is applied to the (2i+1)(2j+1) address as indicated by the equation (13).

Similarly to the R image signals, B image signals  
20 from the image pickup region 120c corresponding to the respective positions of the G image signals calculated using the above equations (6) to (9) are subject to interpolation according to the following equations (14) to (17):

25  $B_{2i2j} = B(i-1)(j-1) \cdot 1/4 + B(i-1)j \cdot 1/4 +$   
 $B i(j-1) \cdot 1/4 + B_{ij} \cdot 1/4 \quad \dots (14)$

$$B_{2i(2j+1)} = B(i-1) \cdot j 1/2 + B_{ij} \cdot 1/2 \quad \dots (15)$$

003290" 49540960

$$B(2i+1)2j = B_i(j-1) \cdot 1/2 + B_{ij} \cdot 1/2 \quad \dots (16)$$

$$B(2i+1)(2j+1) = B_{ij} \quad \dots (17)$$

By the above processing, the R, G, and B signals of 600 × 800 pixels from the image pickup regions 120a, 120b, and 120c are converted into R, G, and B signals of 1200 × 1600 pixels having high definition image quality, respectively.

The high luminance signal generating circuit in the YC processing circuit 230 is a publicly known signal forming circuit for forming a high luminance signal YH from a color signal having the highest spatial frequency component among color component signals. The low luminance signal generating circuit is a publicly known signal forming circuit for forming luminance signal YL of low frequency from a signal containing all the color components of R, G, and B. The chrominance signal generating circuit is a publicly known arithmetic circuit for calculating chrominance signals R-Y and B-Y from highly definition RGB signals.

The recording and reproduction system 30 is a processing system for outputting image signals to the memory and outputting image signals to the liquid crystal monitor 4, and includes a recording processing circuit 300 for writing and reading image signals in and from the memory and a reproduction processing circuit 310 for reproducing image signals read from the memory as output to the monitor. More specifically,

003250"49640960

5

15

25

5 includes an operation detection circuit 410 for  
detecting the operation of the RELEASE button 6, a  
system control unit 400 for controlling the respective  
portions in response to the detection signal and  
generating and outputting timing signals when an image  
0 is picked up and the like, and a drive circuit 420 for  
the solid-state image pickup element 120, which, under  
control of the system control unit 400, generates drive  
signals for driving the solid-state image pickup  
element 120.

Next, operation of the image pickup apparatus according to the present embodiment is described with reference to Figs. 14 and 17A to 17C. First, when the main switch 5 is turned on, power source voltage is supplied to the respective portions and then they become operable. Then, it is determined whether an image signal can be recorded or not in the memory. Here, the number of recordable pictures is displayed on the display area 13 for the remaining number of pictures in a liquid crystal monitor 4 according to the remaining capacity. An operator sees the display and, if a picture is recordable, directs the camera to the field and presses down the RELEASE button 6.



When the RELEASE button 6 is halfway pressed down, the exposure time is calculated. When all the preparatory processing for taking a picture completes, the camera is in a recordable state, and the operator is informed of this through the display. When the RELEASE button 6 is fully pressed down, the operation detection circuit 410 transmits the detection signal to the system control unit 400. Here, the exposure time calculated in advance is counted. When the predetermined exposure time elapses, a timing signal is supplied to the drive circuit 420. Then, the drive circuit 420 generates horizontal and vertical drive signals to sequentially read each of the exposed 1600 x 800 pixels in the horizontal direction and in the vertical direction.

The read signals of respective pixels are converted by the A/D converter 500 into digital signals of a predetermined number of bits to be sequentially supplied to the RGB image processing circuit 210 of the image processing system 20. The RGB image processing circuit 210 carries out interpolation to quadruple the pixel resolution after white balance adjustment and gamma control, and supplies the signals to the YC processing circuit 230.

In the YC processing circuit 230, the high luminance signal generating circuit generates high luminance signal YH with regard to the respective RGB

003290"49640960

pixels, and similarly, the low luminance signal  
generating circuit generates low luminance signal YL.  
The calculated high luminance signal YH is outputted to  
an adder through a low-pass filter. In the same way,  
5 the low luminance signal YL is, after subtraction of  
the high luminance signal YH, outputted to the adder  
through the low pass filter. By this, the difference  
YL-YH between a high luminance signal and a low  
luminance signal is added to obtain an luminance signal  
10 Y. Similarly, the chrominance signal generating  
circuit generates and outputs chrominance signals R-Y  
and B-Y. Components of the outputted chrominance  
signals R-Y and B-Y, which come through the low-pass  
filter, are supplied to the recording processing  
15 circuit 300.

Next, the recording processing circuit 300  
receives the YC signals, compress the respective  
luminance signal Y and chrominance signals R-Y and B-Y  
with a predetermined still image compression method,  
20 and records them sequentially in the memory.

When a still image or a dynamic image is  
reproduced from image signals stored in the memory, the  
PLAY button 9 is pressed down. Then, the operation  
detection circuit 410 detects this operation to supply  
25 a detection signal to the system control unit 400,  
which makes the recording processing circuit 300  
driven. The driven recording processing circuit 300

003290"49640960

Fig. 18 shows another transmission factor distribution of transmission factor distribution type filters provided at positions facing the diaphragm openings 110a, 110b, and 110c of the objective lens 100. The transmission factor changes so as to have multiple steps. The positions where the transmission factor of the transmission factor distribution type filters is the highest are made to correspond to the centers of the diaphragm openings 110a, 110b, and 110c while the positions where the transmission factor is zero are made to correspond to the periphery of the diaphragm openings 110a, 110b, and 110c, respectively. Fig. 19 is a front view of one of the transmission factor distribution type filters. Regions 600, 601, 602, and 603 are formed coaxially with the circular diaphragm opening 110a. The transmission factor decreases in the order of the region 600, the region 601, the region 602, and the region 603.

Such a transmission factor distribution type filter is, similarly to the case of the first embodiment, formed by forming a thin film of Inconel, Chromel, chromium or the like by vapor deposition or sputtering on the light incidence side of the objective

lens 100. The characteristics shown in Fig. 18 can be obtained by making the thin film the thinnest in the center region 600 and thicker toward the periphery in the order of the region 601, the region 602, and the region 603. In forming such a thin film, the position of a mask used in the vapor deposition or sputtering is controlled. The position of the mask is controlled to have steps such that the condition of the vapor deposition or sputtering is the same within each of the regions 600, 601, 602, and 603. As a result, the positions of the mask becomes easy, and thus, the production facilities can be simplified.

If such apodization is carried out, although, strictly speaking, the intensity of the diffraction stripes becomes greater than that of the first embodiment, its influence on the image is small, and thus, the filter of the present embodiment is sufficiently practical.

In case the pixel pitch of the image pickup element is made larger in the attempt to make smaller the size of the memory or to cut the amount of image processing, making high the contrast in a high frequency range becomes less necessary, and thus, the number of the steps of the transmission factor may be decreased as shown in Fig. 20.

Fig. 21 shows a third embodiment of an image pickup apparatus according to the present invention.

008290" 19640960

Similarly to the case of the first embodiment, the diaphragm 110 of an image pickup system 190 has the three circular openings 110a, 110b, and 110c as shown in Fig. 3. Object light which enters the objective lens from them are projected from the three lens portions 100a, 100b, and 100c of the objective lens 100 to form three object images on the image pickup plane of the solid-state image pickup element 120.

The hatched portions 52a, 52b, and 52c sandwiched between the diaphragm 110 and the objective lens 100 are optical filters. As shown in Fig. 4 showing the objective lens 100 viewed from the light incidence side, the optical filters 52a, 52b, and 52c are formed in regions which completely include the diaphragm openings 110a, 110b, and 110c, respectively.

The optical filter 52a has spectral transmission factor characteristics shown as G in Fig. 6 which mainly transmit green, the optical filter 52b has spectral transmission factor characteristics shown as R which mainly transmit red, and the optical filter 52c has spectral transmission factor characteristics shown as B which mainly transmit blue. As the product with the characteristics of the infrared radiation cutting filter formed on the lens portions 100a, 100b, and 100c, the object images formed in the image circles 51a, 51b, and 51c are of green light component, red light component, and blue light component,

respectively.

On the other hand, the optical filters 53a, 53b, and 53c are formed on the three image pickup regions 120a, 120b, and 120c, respectively, of the image pickup element 120. Their spectral transmission factor characteristics are equivalent to the ones shown in Fig. 6. More specifically, the image pickup regions 120a, 120b, and 120c are sensitive to green light (G), red light (R), and blue light (B), respectively.

Since the spectral distributions of the received light of the respective image pickup regions are given as the product of the spectral transmission factors of the pupils and the spectral transmission factors of the image pickup regions, respectively, the combination of the pupil and the image pickup region is selected according to the wavelength range. More specifically, object light which goes through the diaphragm opening 110a is mainly photoelectrically converted in the image pickup region 120a, object light which goes through the diaphragm opening 110b is mainly photoelectrically converted in the image pickup region 120b, and object light which goes through the diaphragm opening 110c is mainly photoelectrically converted in the image pickup region 120c. In other words, the image pickup regions 120a, 120b, and 120c output a G image, an R image, and a B image, respectively.

Since the peak wavelength of the spectral luminous

008290-49640960

efficiency is 555 nm, the signal processing is carried out with a G image signal including this wavelength being as the reference image signal.

INSA 3> The image pickup system 190 takes in three object  
5 images with regard to the three wavelength ranges, and  
thus, compared with an image pickup system provided  
with a mosaic optical filter such as of the Baiyer  
arrangement having the same number of pixels, the focal  
length is about  $1/\sqrt{3}$  times to attain the same image  
10 pickup angle. Therefore, it is necessary to  
materialize image resolution of higher spatial  
frequency component as described in the first  
embodiment.

Further, it is known well that diffraction of  
15 light at a diaphragm opening decreases the contrast in  
an object image. The diffraction stripes can be  
decreased by adding to the objective lens a filter that  
is transparent at the center and becomes darker toward  
the periphery. This addition of the filter is referred  
20 to as apodization. However, generally, in the visible  
wavelength range with regard to a CCD or a CMOS sensor,  
the sensitivity on the side of blue is lower and the  
sensitivity becomes higher toward the long wavelength  
side, and thus, in the third embodiment, it is  
25 determined depending on the wavelength range whether  
apodization is adopted or not.

As described in the above, since the image pickup

008290" 49640960

regions 120a, 120b, and 120c output a G image, an R image, and a B image, respectively, the sensitivity becomes higher in the order of the image pickup region 120c, the image pickup region 120a, and the image pickup region 120b. Accordingly, apodization is adopted only with regard to the diaphragm openings 110a and 110b which corresponds to the image pickup regions 120a and 120b, respectively.

Fig. 21 shows transmission factor distribution type filters 610a and 610b formed on the objective lens. The positions where the transmission factor is the highest are made to correspond to the centers of the diaphragm openings 110a, 110b, and 110c while the positions where the transmission factor is zero are made to correspond to the periphery of the diaphragm openings 110a, 110b, and 110c, respectively. In other words, the transmission factor is distributed so as to be the highest at the centers of the diaphragm openings and so as to monotonically decrease toward the periphery.

Taking into consideration the spectral luminous efficiency characteristics, further simplification may be carried out. The spectral luminous efficiency reaches its peak at 555 nm, and the sensitivity lowers from the peak both on the short wavelength side and on the long wavelength side. It follows that, even if the definition of an R image and a B image is lower than

008290"19670960



that of a G image including the peak wavelength of the spectral luminous efficiency, it is difficult to find a defect for a person who evaluates a color image which is a composite image of the three images. Therefore, apodization is omitted with regard to the diaphragm opening 110b corresponding to the image pickup region 120b for forming an R image, and apodization is adopted only with regard to the diaphragm opening 110a corresponding to the image pickup region 120a. Fig. 22 explains this, and a transmission factor distribution type filter 611a of an image pickup system 191 is formed on the objective lens.

By decreasing the region where the transmission factor distribution type filter is formed, the production process of the objective lens 100 is simplified. This is advantageous from the viewpoint of the cost.

As described in the above, in an image pickup apparatus comprising an image pickup optical system and an image pickup element having a plurality of image pickup regions, wherein a plurality of images corresponding to the plurality of image pickup regions are projected onto the image pickup element through the image pickup optical system, the image pickup optical system is formed so as to have a plurality of imaging systems and the imaging systems are provided with optical filtering means whose transmission factor

becomes smaller as the distance from the optical axis of the imaging system itself becomes longer. Thus, the apparatus of the present invention can attain following effects.

5           (1) An image pickup optical system can be materialized which is suitable for a thin image pickup apparatus and capable of obtaining a high definition image.

10           In addition, an optical filter is constructed such that the transmission factor thereof becomes smaller in multiple stages as the distance from the optical axis of the imaging system becomes longer. Then, the following effect also can be obtained.

15           (2) A simply structured image pickup optical system can be materialized which is suitable for a thin image pickup apparatus and capable of obtaining a high definition image.

20           Further, in an image pickup apparatus comprising an image pickup optical system and an image pickup element having a plurality of image pickup regions, wherein a plurality of images corresponding to the plurality of image pickup regions are projected onto the image pickup element through the image pickup optical system, the image pickup optical system is  
25           formed with an imaging system provided with optical filtering means whose transmission factor becomes smaller as the distance from the optical axis of the

008290" 43640960

imaging system itself becomes longer, and an imaging system which is not provided with such optical filtering means. Thus, the following effect can be also obtained.

- 5 (3) An image pickup optical system can be materialized which is suitable for obtaining a high definition image with regard to a wavelength range having a high spectral luminous efficiency and for compensating for the sensitivity of the image pickup  
10 element with regard to a wavelength range having a low spectral luminous efficiency.

The individual components shown in schematic or block form in the drawings are all well-known in the camera arts and their specific construction and  
15 operation are not critical to the operation or best mode for carrying out the invention.

While the present invention has been described with respect to what is presently considered to be the preferred embodiments, it is to be understood that the  
20 invention is not limited to the disclosed embodiments. To the contrary, the invention is intended to cover various modifications and equivalent arrangements included within the spirit and scope of the appended claims. The scope of the following claims is to be  
25 accorded the broadest interpretation so as to encompass all such modifications and equivalent structures and functions.

008290"19640960

For example, in the described embodiments, optical filters used for the color separation are primary color filters of red, green, and blue. However, the present invention is also applicable to a case where these  
5 filters are replaced by complementary color filters of cyan, magenta, and yellow.

Further, in the above embodiments, an object image having the highest luminosity factor (green) is used as a reference to describe change in the intervals between  
10 the object image having the highest luminosity factor and object images having other luminosity factors (other colors), which is caused by change in the distance to the object. However, the present invention is also applicable to a case where an object image  
15 having the highest luminosity factor (green) is not used as the reference.

It is to be noted that, in the present invention, the respective embodiments in the above or technical elements thereof may be freely combined depending on  
20 the situation.

Also, in the present invention, the whole or part of the appended claims or of the structure of an embodiment may form one apparatus, may be combined with another apparatus, or may be an element of an  
25 apparatus.

008290"49640960